MESSTEC Power Converter GmbH

Data Sheet Fast Modulator MSM 60-25



Features

Drives arbitrary current waveforms into laser diodes CW, pulsed, modulated or mixed curves Short rise and fall time Two analog inputs plus BIAS current

Small dimensions, low weight



Diode current CW 0 ... 60 A

Diode current pulsed 0 ... 120 A (short pulses)

Diode voltage 0 ... 23 V
Output power 1440 W max
Power dissipation 90 W max allowed

 $\begin{array}{lll} \text{Supply voltage} & 1 \text{ V } ... \text{ 24 V} \\ \text{Supply current} & 60 \text{ A max} \\ \text{Supply voltage*} & 3 \text{ V } ... \text{ 6 V} \\ \text{Rise time} & 5 \text{ } \mu \text{s} \\ \text{Fall time} & 7 \text{ } \mu \text{s} \\ \end{array}$

Frequency (set point 1) 100 kHz max Frequency (set point 2) 100 kHz max

Inputs

Diode current set point 1 0 ... 500 mV (50 Ohm input)
Diode current set point 2 0 ... 5 V (high impedance)

Enable TTL Reset TTL

Outputs

Diode current monitor 0 ... 50 mV (into 50 Ohm) Temperature 0 ... 4 V for 0 ... 80°C

Ready TTL Excess temperature TTL

General specifications

 $\begin{array}{lll} \mbox{Ambient temperature} & 0 \dots + 45 \ ^{\circ}\mbox{C} \\ \mbox{Cooling} & \mbox{Required} \\ \mbox{Dimensions} & 95 \ x \ 61 \ x \ 20 \ mm \end{array}$

Weight 240 g Ordering Code 10100452

* for internal electronics

Description

The fast diode current modulator MSM 60-25 is a linear modulator with improved properties for driving arbitrary current waveforms or fast pulses into laser diodes. Current waveforms can be CW, pulsed, modulated or mixed with frequencies up to 100 kHz and currents up to 60 A for CW and 120 A for pulsed waveforms. The modulator is small and compact and it is designed for mounting with low inductance at laser diodes or for integrating in laser diode modules. It has two analogue inputs for the current set point: a high frequency input (50 Ohm input impedance) with a bandwidth of 100 kHz and a low frequency input with a bandwidth of 100 KHz. Additionally there is a 10 turns potentiometer for generating a CW-current (bias current). All set points are added and build the effective current set point.

Technical subjects to change without notice.

Document: 10100452	Revision: 000	Date: 24.11.2014
www.powerconverter.eu	info@powerconverter.eu	+49 (0) 8856 803060

